



Registered Office:
125 Louis St, South Hackensack, NJ 07606, United States

15 User Pico G3 Kit Specifications:

DEVICES: Pico G3

Operating system
Android

System architecture/processor
Qualcomm Snapdragon XR2
CPU - Octa-core Kryo 585 (1 x 2.84 GHz, 3 x 2.42 GHz, 4 x 1.8 GHz)
GPU - Adreno 650

Memory (RAM)
6GB

Storage (ROM)
128GB

Dimensions
Height: 4.4 in
Width: 7.5 in
Length: 4.9 in

Weight
604g

Display
4K Resolution (3664 x 1920)

Battery
5300mAh

Connectivity
USB - C, 3.5 mm headset jack

Bluetooth® technology
Yes

Wi-Fi
Yes

Speakers/microphones
Integrated stereo speakers
Mic



Tablet (Lenovo Tab 4 Plus 10)

Product Dimensions: 9.7 in x 6.7 in x 0.3 in

Screen Size: 10.1 inches

Screen Resolution: 1920 x 1080 Pixels

Multi-touch Capacitive-type multi-touch, support 10-point touch

Qualcomm MSM8917 Snapdragon 425 (28 nm) (Wi-Fi/LTE model)

Processor Count 4

RAM Size 2 GB

Maximum Memory Supported 64 GB

Storage 16 GB

Hard Disk Technology SSD



Case Dimensions

Product Dimensions 34.2 in x 22.4 in x 14.5 in
Weight Full 61.7 lbs
Weight Empty 50.7 lbs

DUAL BAND ROUTER (TP-Link AX10)

Archer AX10 comes equipped with the latest wireless technology, Wi-Fi 6, for faster speeds, greater capacity, and reduced network congestion.

Archer AX10 dual-band router reaches even faster speeds up to 1.5 Gbps (1201 Mbps on 5 GHz band and 300 Mbps on 2.4 GHz band).

INCHARGE CASE (C06)

VR cases and Parotec specifications of electrics. Parotec Approvals:

CE Approved

ISO 9001 registered (2008)

Solutions based around our 16 & 36 x Port PCB Intelligence Board have been subject to testing at Cass Industries Limited an compliance testing and CE marking partner for UK & EU requirements.

Parotec PCB Boards:

PCB Inner board Power consumption:

5V @ 34A maximum supply (each port is current limited to 2.1A)

Robust design with up to 35 possible fixing holes on uniform 25mm centres

IEC/EN 60335 compliant and CE certified

Input voltage required up to 5.3V

Charge & Sync version of PCB also UL (USA) approved

*Charge Only boards currently used for VR kits. IF sending to US we would add Charge & Sync PCB's.

Parotec: Explorer Cases. Used to house all VR Kit.

Where no modification to the physical case is made these are fully waterproof and dust free.

Where we may have added external cooling fans the cases are reduced to weather proof and dust free.

